



New  
Energy  
Systems

Custom Energy Storage Systems



## NES-I AC-Connect

Rectifier module for connecting AC power sources

Available in a variety of sizes, the NES-I AC-Connect is designed to connect AC power sources - e.g. emergency power generators, co-generators and power grids - to the NES-I system. Connecting several devices in parallel makes it possible to achieve even higher power outputs.

### Key Features

- ✓ Very high maximum efficiency of 95 %
- ✓ Can be connected in parallel for even greater outputs
- ✓ Simple installation, set-up and operation





## Technical Data



NES-I AC-Connect*	5 l	10 l
Rated supply voltage (V)	230 V	230/400 V
Rated frequency (Hz)	50	50
Rated output (W)	5	10

(for Unom. f.nom/25 °C/cos =1)

Mechanical Dimensions	5 l	10 l
Width x height x depth (cm)	50x65x50	50x65x50
Weight (kg)	44	98

Environmental Conditions	5 l	10 l
Ambient temperature °C	-25 to 60	-25 to 60
Protection class	IP 21	IP 21

\* Products and services as well as technical data are subject to change, this includes any change as a result of country-specific legislation. NES-GmbH is not liable for any mistakes or printing errors.

### NES-GmbH

Haidenholzstr. 69  
83071 Stephanskirchen  
Germany

Tel.: +49 8036 6740-454

Fax: +49 8036 6740-452

E-mail: [info@newenergy-systems.com](mailto:info@newenergy-systems.com)

[www.newenergy-systems.com](http://www.newenergy-systems.com)

Your certified NES-partner